**Accelerating the next technology revolution**

# Understanding the mechanism of capping layer damage and development of a robust capping material for 16 nm HP EUV mask

Il-Yong Jang [1], Arun John [1], Frank Goodwin [1]

Su-Young Lee[2], Seong-Sue Kim[2]

[1] SEMATECH
[2] Samsung Electronics

# Outline

- Current status
- Experimental conditions
- Cause of Ru damage
- Simulation results
- How to mitigate Ru damage
  - Process improvement
  - Development of new material
- Summary

# Ru damage



Absorber pattern(Ta)

Capping layer

Multi layer (Mo/Si)

Substrate (LTEM)

. **Protect ML from damage**
  : Dry Etch, Repair, Cleaning
. **Requirements**
  : High EUV reflectance
  : Oxidation resistance
  : Durability in plasma and chemical
  : Stability in high temperature

→ **Ru/Ru-compound for capping layer**

**Ru damage**

. **Mask process**
  : Physical force
  : Chemical reaction
  : High temperature
  : UV radiation
  : Oxidation

2μm

. **Results**
  : ML oxidation
  : Reflectivity drop
  : CD change in WF

# Ru damage during mask process

**Blank Supplier**

Substrate $\longrightarrow$ ML deposition $\longrightarrow$ Capping layer ① deposition

$\longrightarrow$ **Annealing** ② $\longrightarrow$ Absorber deposition

**Maskshop**

Resist patterning $\longrightarrow$ Absorber etch ③ $\longrightarrow$ **Cleaning** ④

$\longrightarrow$ Inspection $\longrightarrow$ Repair

① **Properties of capping layer**
  : Properties of material in mechanical and chemical stress

② **Annealing in High temperature**
  : Oxidation, change in material properties

③ **Plasma etch** : oxidation, erosion by corrosive gas, stress by ion bombardment

④ **Cleaning process**
  : Oxidation, change in material properties

# Experimental

- **Material**
  - **6 inches sq. wafer for deposition of Ru and new capping material**
  - **Reactive sputtering using SEMATECH's IBD chamber**
- **Process**
  - **In-situ. UV(IUV) cleaning at Mask Track, Anneal on hotplate**
- **Analysis : Angle Resolved XPS, Four point probe**

① Norminal incident

②Min. incident angle

Detectable range of AR-XPS

$\Theta_1 = 23degs$

$\Theta_2 = 83degs$

③Max. incident angle

$\cos \Theta_2 = 0.49nm$

Oxide

$\cos \Theta_1 = 3.68nm$

Ru

Norminal angle:4nm

Si

Fine

Sheet resistance($\Omega$/cm)

Damaged

# Change in film properties

# Oxidation by annealing

**O core**



**Si core**





- **Conditions :** 2.5nm-Ru, 10 min annealing, 3.5nm-probing depth

- **O core** : Annealing Temp ↑ → RuOx gradually ↑ → **Ru oxidation (RuO$_2$)**

- **Si core** : The SiOx peak (101.97eV) abruptly increase from 200°C.

  Si has been changed to SiOx by oxygen penetration

➔ **Ru and Si are oxidized by high temperature annealing process**

# Oxidation by IUV cleaning



- **Conditions** : 2.5nm-Ru, IUV cleaning (5X, 10X, 50X cycles), 3.5nm-probing depth
- Ru appears to be strongly oxidized by IUV cleaning
- Si under the Ru is also oxidized by IUV cleaning

➔ **During IUV process, oxygen penetrates Ru and finally reacts with Si**

# Mechanism of Ru damage



. **Mask is annealed in Air with HT and cleaned in IUV+DI**
. **Oxygen diffuses to the surface**
. **Clear region**
  - Oxygen penetrates Ru film and reaches Si surface
    : Ru → RuOx (ductile → brittle)
    : **Si → SiOx**
. **Dark region**
  - Absorber protects oxygen penetration

. **Volume expansion when Si → SiOx**

$$x_{si} = x_{ox} * \frac{N_{ox}}{N_{si}}$$

$$= x_{ox} * \frac{2.3*10^{22}\ molecules/cm^3}{5*10^{22}\ molecules/cm^3} = 0.46 x_{ox}$$



. **Tensile stress**

. **Properties change**
  - RuOx : brittle in stress
  - SiOx : Poor adhesion to Ru

# Simulation of the Ru damage

## Simulation parameter

- **S/W: ABAQUS (Finite Element Method)**
- **Element: four-node quadrilateral elements**
- **Unit element size(W x H): 1 nm x 1 nm**
- **Total number of Nodes: 37,756ea**
- **Total number of elements: 37,000ea**
- **Total Degree of Freedom: 75,512ea**

| Layer | Mate-rial | Thick (nm) | Width (nm) | Young's Modulus (GPa) | Poisson's ratio |
|-------|-----------|------------|------------|------------------------|------------------|
| Abs | TaN | 70 | 200 | **186** | **0.34** |
| Cap | Ru | 2.5 | - | **447** | **0.30** |
| Si | Si | 4.1 | - | **188** | **0.28** |

## Boundary condition

Boundary condition: 1-D D-G model $\quad x \cong \dfrac{B}{A}(t+\tau)$



Absorber

bottom(Fixed Y-dir.)    Umeshmotion area    Ru Capping    Top-Si

# Simulation of the Ru damage

Film stress

Displacement



**Stress at edge : 5 x 10$^{-8}$ Pa**

**\*Gap: 0.529nm**

S, Mises
(Avg: 75%)
+5.444e-08
+4.990e-08
+4.537e-08
+4.083e-08
+3.629e-08
+3.176e-08
+2.722e-08
+2.268e-08
+1.815e-08
+1.361e-08
+9.074e-09
+4.537e-09
+2.097e-14

U, U2
+1.529e+00
+1.476e+00
+1.423e+00
+1.370e+00
+1.316e+00
+1.263e+00
+1.210e+00
+1.157e+00
+1.104e+00
+1.050e+00
+9.973e-01
+9.441e-01
+8.909e-01

**\*umeshmotion: 1 nm (4.1→5.1 nm)**

# How to mitigate?

# Mitigation of Ru damage – by process

**. Annealing in vacuum**
- No significant SiOx peak
  → suppress Si oxidation
- Slight shift of Si peak due to RuSix formation

**. Annealing in Low Temp. (@150°C)**
- No significant SiOx peak
- Critical Temp. trigger oxidation of Si should be between 150°C and 200°C
- Less RuSix formation

**. $H_2$ dosing**
- Impossible to reduce the oxidized Si by $H_2$ flow
- Increases in peak intensity due to removal of carbon contamination



SiOx ◄---  ----► Si

③ No peak shift

Annealed in Air
Annealed in Air(H2 dosed)
Annealed in LT
Annealed in Vac
Ru

② shift due to RuSix

① Si

# Mitigation of Ru damage – by new material



**. Capping layer**
- Suppress oxygen penetration
- Less oxidation
- Stable in chemical / plasma
- Ductile in mechanical stress
- No deterioration of optical properties
- Robust in mask process
- $B_4C$, new Ru compound

**. Buffer layer**
- Suppress oxygen penetration
- Less oxidation
- Robust in mask process
- Good adhesion btw Si and capping layer
- No deterioration of optical properties
- Ru/BL/top-Si

# B$_4$C capping layer

Reflectivity for 40 bilayer Mo/Si bilayers with different B4C interlayers



Reflectivity
- 66.50%-67.00%
- 66.00%-66.50%
- 65.50%-66.00%
- 65.00%-65.50%
- 64.50%-65.00%
- 64.00%-64.50%

. Good barrier layer to suppress the inter-diffusion
. No silicide formation → increase in 2% of EUVR



Ru -2.5nm
B$_4$C - 2.5nm



- B4C(Annealed in Air)
- Ru(Annealed in Air)
- Ru

① Si
② Rich RuSix
③ RuSix
SiOx

**. No EUVR deterioration is observed once B$_4$C is used as a capping layer instead of Ru**

# New Ru compound capping layer



- Dosed "A" atom in Ru to suppress change in film property
- The amount of Si oxidation is inversely proportional to the amount of incorporated "A" atom in RuA

# Inserting buffer layer



. SEMATECH has developed a buffer layer between Ru and Si
. The purpose of buffer layer is to suppress the oxygen diffusion to Si
. The Ru/BL/top-Si structure increases the durability of Ru in IUV process
. Further optimization should be necessary for this structure.

# Summary

**Normalized durability**



. SEMATECH has disclosed the root cause of Ru damage and been developing a new material with state-of-the art IBD tool to solve the problem.
. The most promising method will be verified on 6 in. sq. mask using mask shop's infrastructure in near future.

# Acknowledgement

. **Deposition** : Patrick Kearney and Alin Antohe from SEMATECH

. **XPS analysis** : Prof. Carl Ventrice Jr. and Tyler Mowll from CNSE

. **FEM simulation** : Prof. YongHoon Jang from Yonsei Univ.

**Thank you !**